

**WiFi Module**

# **BMC81M001 User Guide**

Revision: V1.00    Date: April 25, 2023


[www.bestmodulescorp.com](http://www.bestmodulescorp.com)

## Contents

<b>Introduction .....</b>	<b>3</b>
<b>Features .....</b>	<b>3</b>
<b>Block Diagram .....</b>	<b>4</b>
<b>Pin Description .....</b>	<b>4</b>
<b>Technical Specifications .....</b>	<b>5</b>
Recommended Operation Conditions .....	5
Timing Specifications .....	5
<b>Hardware Overview .....</b>	<b>6</b>
Power Supply .....	6
LED .....	7
Communication Interface .....	7
<b>Application Circuit .....</b>	<b>7</b>
<b>Dimensions .....</b>	<b>8</b>

## Introduction


The BMC81M001 is a WiFi module from Best Modules. It includes an integrated ESP-12F module. The module supports wireless standard IEEE802.11 b/g/n protocol and complete TCP/IP protocol stack. Users can use this module to add a network function for existing devices or to build an independent network controller. The module uses the BMCOM interface and UART communication method to implement WiFi configuration and data transparent transmission. The module is suitable for use in smart home, Internet of things and other field applications.




## Features

- Operating voltage: 3V~5.5V
- Operating current
  - ◆ Transmit data: 180mA @ 3.3V/11Mbps
  - ◆ Receive data: 60mA @ 3.3V/70dBm
- Standby current: 4mA @ 3.3V
- Integrated WiFi module: ESP-12F
  - ◆ Wireless protocol: 802.11b/g/n
  - ◆ Spectrum range: 2400~2483.5MHz
- Communication interface:
  - ◆ BMCOM×1 (NC, RX, TX, VDD, GND)
  - ◆ Communication method: UART (baud rate: 115200bps)
- Provides Arduino Library support
- Module size: 50mm×35.3mm×7.5mm

## Block Diagram



## Pin Description



BMCOM pins:

Pin	Function	Description
1	NC	—
2	RX	UART receiving data line
3	TX	UART transmitting data line
4	VDD	Positive power supply
5	GND	Negative power supply, ground

## Technical Specifications

### Recommended Operation Conditions


Ta=25°C

Symbol	Parameter	Conditions	Min.	Typ.	Max.	Unit
V <sub>DD</sub>	Input voltage	—	3	3.3	5.5	V
I <sub>DD</sub>	Operating Current	Transmit data, 3.3V @ 11Mbps	—	180	—	mA
		Receive data, 3.3V @ 70dBm	—	60	—	mA
I <sub>STB</sub>	Standby Current	V <sub>DD</sub> =3.3V	—	4	—	mA



### Timing Specifications

Ta=25°C


Symbol	Parameter	Conditions	Min.	Typ.	Max.	Unit
t <sub>DEL-RSP</sub>	Response Delay Time	Has response only	—	2	—	ms
		Has response and data	—	—	1	s
t <sub>INR</sub>	Interval Time	—	—	200	—	ms



## Hardware Overview



## Power Supply



- BMCOM pin: provided by the VDD input, 3V~5.5V.

It is recommended that the external power supply current must be greater than 500mA.


## LED

- PWR: power indicator


## Communication Interface

- Communication method: UART
- Baud rate: 115200bps
- Communication logic reference voltage: 3V~5.5V
- Communication protocol:
  - ◆ The detail instruction description and communication protocol can refer the ESP8266 official AT instruction set.

## Application Circuit



## Dimensions



**Dimension Information**

NO.	Unit	mm	inch
A		32.6	1283.54
B		22.69	893.21
C		12.53	493.21
D		2.65	104.33
E		44.7	1760
F		2.54	100
G		6.35	250
H		30	1180.67
I		35.25	1387.87
J		2.27	89.37
K		7.5	0.295
L		55	2.165
W		23.94	943.91
D1		0.9	35.43
D2		2.2	86.61

**Dimension List**



Copyright© 2023 by BEST MODULES CORP. All Rights Reserved.

The information provided in this document has been produced with reasonable care and attention before publication, however, BEST MODULES does not guarantee that the information is completely accurate. The information contained in this publication is provided for reference only and may be superseded by updates. BEST MODULES disclaims any expressed, implied or statutory warranties, including but not limited to suitability for commercialization, satisfactory quality, specifications, characteristics, functions, fitness for a particular purpose, and non-infringement of any third-party's rights. BEST MODULES disclaims all liability arising from the information and its application. In addition, BEST MODULES does not recommend the use of BEST MODULES' products where there is a risk of personal hazard due to malfunction or other reasons. BEST MODULES hereby declares that it does not authorise the use of these products in life-saving, life-sustaining or safety critical components. Any use of BEST MODULES' products in life-saving/sustaining or safety applications is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold BEST MODULES harmless from any damages, claims, suits, or expenses resulting from such use. The information provided in this document, including but not limited to the content, data, examples, materials, graphs, and trademarks, is the intellectual property of BEST MODULES (and its licensors, where applicable) and is protected by copyright law and other intellectual property laws. No license, express or implied, to any intellectual property right, is granted by BEST MODULES herein. BEST MODULES reserves the right to revise the information described in the document at any time without prior notice. For the latest information, please contact us.